

ELECTRIC MIXER

■
The heart of our mixer line is a combination of revolutionary ergonomic design, sturdy mechanicals and torque feedback electronics. These combine to make our mixers the most effective and comfortable mixers available anywhere.

■
The unique handle design results in the perfect hand position with 15 degree tilt for fatigue-free operation. The rubber grip areas help provide maximum comfort. Ergonomics at its best!

■
The torque feedback function allows maximum torque to be maintained at any speed. Changing the speed without leaving the handles is easy with the speed adjustor thumb wheel. This allows the machine to mix at maximum efficiency with any kind of media.





Model	H-EV160	H-EV52	H-EV42	H-EV32
Power Input	1600W	1300W	1100W	800W
Voltage	110-120V~ 50-60Hz, 220-240V~ 50-60Hz			
No Load min-1	180-350 / 280-550	150-400 / 250-700	250-700	750
N-m (Low Gear / High Gear)	42.7 / 29.9	27.4 / 17.3	11.0	6.0
Number Of Gears	2	2	1	1
Amps (110V)	14.50	10.90	10.00	7.20
Amps (230V)	7.00	5.20	4.80	3.60
Thread For Fixing The Tool	M14 x P2.0	M14 x P2.0	M14 x P2.0	M14 x P2.0
Mixing Paddle (Max.)	160mm (6-5/16 in.)	140mm (5-1/2 in.)	120mm (4-11/16 in.)	105mm (4-1/8 in.)
Electronic Speed Control	With	With	With	N/A
Dimensions(Motor unit only)	350mm x 322mm x 190mm	345mm x 322mm x 190mm	322mm x 312mm x 190mm	322mm x 250mm x 190mm
Net Weight	5.6 kg (12.3Lbs)	4.1kg (9Lbs)	3.6 kg (7.9Lbs)	2.9 kg (6.4Lbs)